

7NT CITICEL® Nitric Oxide (NO) Gas Sensor Part Number: AF704-400

Product Data Sheet

Product Datasheet

7NT Nitric Oxide Sensor

Document Purpose

The purpose of this document is to present the performance specification of the 7NT nitric oxide gas sensor.

This document should be used in conjunction with the Operating Principles (OP09) and the Product Safety Datasheet (PSDS 5).

The data provided in this document are valid at 20°C, 50% RH and 1013 mBar for 3 months from the date of sensor manufacture.

Output signal can drift below the lower limit over time. For guidance on the safe use of the sensor, please refer to the Operating Principles (OP09).

Doc. Ref.: 7nt.indd Issue 7 ECN I 4791

27th March 2017

CITY TECHNOLOGY ENGINEERING SAFETY



Product Data Sheet

Key Features & Benefits:

- Robust, industry standard 7-Series packaging
- **Compact Size**

Technical Specifications

MEASUREMENT

Operating Principle | 3-electrode electrochemical Measurement Range

Maximum Overload

Filter | None

Sensitivity*

Response Time (T_{so})*

Baseline Offset (clean air)* Zero Shift (+20°C to +40°C)

Resolution

Repeatability | 2% of signal

0-100 ppm NO 1500 ppm NO

 $0.55 \pm 0.11 \,\mu\text{A/ppm}$

<15 Seconds

0 to +3 ppm NO equivalent < 9 ppm NO equivalent 0.5 ppm (when used with

recommended electronics)

Linearity Linear

ELECTRICAL

Recommended Load Resistor 10 Ω

Bias Voltage +300 mV

MECHANICAL

Weight 17 g

Housing Material:

Polycarbonate Cap

ABS Body Orientation | Any

ENVIRONMENTAL

Operating Temperature Range | -20°C to +50°C Recommended Storage Temp | 0°C to 20°C

Operating Pressure Range | Atmospheric ± 10% Pressure Coefficient | 0.016% signal/mBar


Operating Humidity Range | 15 - 90% RH non-condensing


LIFETIME

Long Term Sensitivity Drift | <2% signal loss/month **Expected Operating Life** Two years in air

Storage Life 6 months in CTL container

Product Dimensions





All dimensions in mm All tolerances ±0.15 mm unless otherwise stated

IMPORTANT NOTE: Connection should be made via PCB sockets only. Soldering to the pins will seriously damage your sensor.

* Specifications are valid at 20°C, 50% RH and 1013 mBar, using City Technology recommended circuitry. Performance characteristics outline the performance of sensors supplied within the first 3 months. Output signal can drift below the lower limit over time.

Doc. Ref.: 7nt.indd Issue 7 ECN I 4791

27th March 2017

Page 2 of 3





Product Data Sheet

Poisoning

CiTiceLs are designed for operation in a wide range of environments and harsh conditions. However, it is important that exposure to high concentrations of solvent vapours is avoided, both during storage, fitting into instruments and operation.

When using sensors with printed circuit boards (PCBs), degreasing agents should be used before the sensor is fitted. Do not glue directly on or near the CiTiceL as the solvent may cause crazing of the plastic.

Cross Sensitivity Table

Whilst CiTiceLs are designed to be highly specific to the gas they are intended to measure, they will still respond to some degree to various other gases. The table below is not exclusive and other gases not included in the table may still cause a sensor to react.

IMPORTANT NOTE: The cross sensitivity data shown below does not form part of the product specification and is supplied for guidance only. Values quoted are based on tests conducted on a small number of sensors and any batch may show significant variation. For the most accurate measurements, an instrument should be calibrated using the gas under investigation.

Gas	Concentration Used (ppm)	7NT (ppm NO)
Carbon Monoxide, CO	300	0
Hydrogen Sulfide, H_2S	15	≈ 5
Sulfur Dioxide, SO ₂	5	0
Nitrogen Dioxide, NO ₂	5	< 1.5
Nitrous Oxide, N ₂ O	100	0
Chlorine, Cl ₂	1	0
Hydrogen, H ₂	100	0
Hydrogen Cyanide, HCN	10	0
Hydrogen Chloride, HCl	5	< 1
Ethylene, C ₂ H ₄	100	0

SAFETY NOTE

This sensor is designed to be used in safety critical applications. To ensure that the sensor and/or instrument in which it is used, are operating properly, it is a requirement that the function of the device is confirmed by exposure to target gas (bump check) before each use of the sensor and/or instrument. Failure to carry out such tests may jeopardize the safety of people and property.

Every effort has been made to ensure the accuracy of this document at the time of printing. In accordance with the company's policy of continued product improvement City Technology Limited reserves the right to make product changes without notice. The products are always subject to a programme of improvement and testing which may result in some changes in the characteristics quoted. As the products may be used by the client in circumstances beyond the knowledge and control of City Technology Limited, we cannot give any warranty as to the relevance of these particulars to an application. It is the clients' responsibility to carry out the necessary tests to determine the usefulness of the products and to ensure their safety of operation in a particular application.

Doc. Ref.: 7nt.indd Issue 7 ECN I 4791

27th March 2017

Page 3 of 3

